


Creating FSM Mnemonic Maps in SimVision

An application note from
Team genIES





Creating FSM Mnemonic maps in SimVision

- Problem
 - Verilog FSMs do not show up as enumerated types in SimVision's waveform window, so the user has to define their own mnemonic map.
- Solution
 - Use create_mmap.tcl as an extension to ncsim, to semi-automate the mmap creation.
- *Here's how...*



Installation

- Download tcl script from https://www.cadence.com/Community/CSSharedFiles/blogs/fv/genIES/SimVision%20FSM/create_mmap.tcl
- Put the following command into your .simvisionrc file


```
source create_mmap.tcl
```

 - You should see the message “Loaded create_mmap function” when SimVision starts up
 - You will see a new button called “FSM Map” in the DesignBrowser toolbar




Use model

- Each time you want to create a new FSM mmap
 - Use the Design Browser / Source Browser to select
 - The FSM state variable
 - All the parameter / localparam objects that enumerate the state
 - When all objects are highlighted, click the “FSM Map” toolbar button to create the mmap.
- The new mmap is
 - Created instantly in SimVision (and the state variable is sent to the waveform)
 - Saved to a new *.svcf file so you can reload it in any SimVision session
 - Named `<module>__<statevar>`, where `<module>` is the enclosing module's name, and `<statevar>` is the name of the state variable.



1. Select the enumeration parameters and the FSM state variable

2. Click the button to create the new mmap





Notes

- Any state enumeration name that contains the word “error” will be recognised and the mmap style extended to show red text and line colour
 - Users may enhance the TCL pattern matching to recognise other name patterns and apply other styles
- Note that SimVision automatically recognises SystemVerilog enumerated types
- Email genIES@cadence.com if you have any questions



cā dence™

